



## FUNCTIONS:

1. Set limits automatically based on obstacle detection.
2. Obstacle detection stop available, and motor will recognise the stop position as new limit.
3. Pull fabric to start motor.
4. Hold on motor's program button for 10 seconds to delete limits.

MODEL NUMBER	WSCMXG-AC-1.2
RATED TORQUE (Nm)	1.2
MAXIMUM PULLING WEIGHT (kg)	50
RUNNING SPEED (cm per second)	9
NOMINAL VOLTAGE (V)	AC 110-240V
NOMINAL CURRENT (A)	0.1
NOMINAL POWER (W)	18
RUNNING TIME	S2: 12 min
PROTECTION INDEX (IP)	IP 40
TOTAL LENGTH (mm)	260
MAXIMUM TURNS	INFINITY
NET WEIGHT (kg)	1
RS-485 COMPATIBLE	NO
RELAY OR SWITCH CONTROL	YES
NUMBER OF WIRES	4
CONTROL METHODS	Connect to an external switch, or connect to an Alpha receiver to be controlled by remote.